

Astérisque

HENRY HERMES

Lie algebraic methods for the control of infinite dimensional nonlinear evolution equations

Astérisque, tome 75-76 (1980), p. 125-131

http://www.numdam.org/item?id=AST_1980__75-76__125_0

© Société mathématique de France, 1980, tous droits réservés.

L'accès aux archives de la collection « Astérisque » (<http://smf4.emath.fr/Publications/Asterisque/>) implique l'accord avec les conditions générales d'utilisation (<http://www.numdam.org/conditions>). Toute utilisation commerciale ou impression systématique est constitutive d'une infraction pénale. Toute copie ou impression de ce fichier doit contenir la présente mention de copyright.

NUMDAM

Article numérisé dans le cadre du programme
Numérisation de documents anciens mathématiques
<http://www.numdam.org/>

LIE ALGEBRAIC METHODS FOR THE CONTROL OF INFINITE DIMENSIONAL NONLINEAR EVOLUTION EQUATIONS

by

Henry HERMES*

-:-:-:-

INTRODUCTION. -

Let $\mathcal{A}$, $\mathcal{B}$ be densely defined operators acting within a Banach space B of $\mathbb{R}^n$ valued functions. We consider systems of the form

$$(1) \quad dv_t/dt = \mathcal{A}(v_t) + u(t) \mathcal{B}(v_t), \quad v_0 = \varphi \in B$$

where the control u is Lebesgue measurable with values $|u(t)| \leq 1$, and unique solutions of (1) are assumed to exist for small $t > 0$. An observation of (1) is a continuous linear map $g : B \rightarrow \mathbb{R}^k$.

Let v_t denote the reference solution, at time t , corresponding to control $u \equiv 0$, and $A(t, \varphi) \subset B$ be the set of points attainable at time t by all solutions of (1). We shall study two questions. The first, that of local controllability, is to derive computable conditions to determine when $g(v_t) \in \text{interior } g(A(t, \varphi))$ for small $t > 0$. This includes the study of $\mathbb{R}^n$ controllability, say for delay equations, but not function space controllability, e.g. see [1], [4]. The second question is that of finite dimensional realizations. Specifically, if $t \mapsto g(v_t(u))$ is a solution $t \mapsto v_t(u)$ of (1), we say g admits a strong differential realization on $\mathbb{R}^k$. We shall give an example of an observation of a linear controlled parabolic equation which admits a strong (bilinear) differential realization on $\mathbb{R}^2$. This realization has "singular arcs" which may be studied by high order methods using Lie Theory. This illustrates the difficulties which may occur in "internally

* This research was supported by NSF grant MCS 76-04419-A01.

controlled" systems of partial differential equations, i.e. systems where the control is not a forcing function or boundary value.

I. - LIE PRODUCTS OF OPERATORS.

Throughout, the symbol s will be used as the independent variable for a function $v \in B$. The infinitesimal generators we will consider shall be assumed to have the form

$$(2) \quad (Cv)(s) = f^s((T^s v)(s))$$

where for each s , T^s is a closed linear operator acting within B (and these may change with the value s) while $f^s: \mathbb{R}^n \rightarrow \mathbb{R}^l$ is real analytic. We assume, throughout, that our operators generate (at least locally) strongly continuous one parameter semi-groups, i.e., that $dv_t/dt = C(v_t)$, $v_0 = \varphi$ has a unique solution for small $t > 0$.

For example, consider the delay equation on $\mathbb{R}^n$; $dx(t)/dt = W(x(t-1))$, $x(s) = \varphi(s)$, $-1 \leq s \leq 0$ where $\varphi \in C[-1, 0]$ and $W: \mathbb{R}^n \rightarrow \mathbb{R}^n$ is real analytic. Let $\zeta(t, \varphi)$ denote a solution at time t and define $v_t(\varphi)(s) = \zeta(t+s, \varphi)$, $-1 \leq s \leq 0$. The map $t \rightarrow v_t(\varphi) \in C[-1, 0]$ is a strongly continuous semi-group with infinitesimal generator

$$(Cv_t)(s) = \begin{cases} d/ds v_t(s) = d/dt v_t(s), & -1 \leq s < 0 \\ W((Sv_t)(0)) = W(v_t(-1)), & s = 0 \end{cases}$$

where S is the unit shift operator (i.e. $(Sv)(t) = v(t-1)$). Here, referring to (2), $f^s(\lambda) = \lambda$ and $T^s = d/ds$ if $-1 \leq s < 0$ while $f^s(\lambda) = W(\lambda)$ and $T^s = S$ if $s = 0$. In the Banach space $B = C[-1, 0]$, $v_t(\varphi)$ satisfies the equation $d/dt v_t(\varphi) = C(v_t)$, $v_0 = \varphi$. Let C be an operator of the form (2) and f' denote the derivative of f . We define $((DC(v)(s))w)(s) = f'^s((T^s v)(s))(T^s w)(s)$ and the Lie Product of operators $C, \mathcal{G}$ of the form (2) as $([C, \mathcal{G}](v))(s) = ((DC(v)(s))(\mathcal{G}v))(s) - ((D\mathcal{G}(v)(s))(Cv))(s)$. As expected, if $C, \mathcal{G}$ are linear operators then $[C, \mathcal{G}]$ is just the commutator $C\mathcal{G} - \mathcal{G}C$. Furthermore, the above concepts easily generalize to operators of the form $(Cv)(s) = \sum_{\nu=1}^m f_{\nu,1}^s((T_{\nu,1}^s v)(s)) \dots f_{\nu,k}^s((T_{\nu,k}^s v)(s))$; the details and examples of computations can be found in [4], [5]. We introduce the notation $(ad C, \mathcal{G}) = [C, \mathcal{G}]$ and inductively $(ad^{k+1} C, \mathcal{G}) = [C, (ad^k C, \mathcal{G})]$.

Now consider the equation (1) with $\mathcal{A}, \mathcal{B}$ operators of the form (2). Let $\eta_t(\varphi)$ denote the solution, at time t , of $dv_t/dt = \mathcal{A}(v_t)$, $v_0 = \varphi$, and $D\eta_t(\varphi)$ the differential of the map $\varphi \rightarrow \eta_t(\varphi)$. In [4] we showed the

DECOMPOSITION THEOREM. - Assume the maps $t \rightarrow \eta_t(\varphi)(s)$ and $t \rightarrow D\eta_t(\varphi)(s)$ are real analytic for all s and that $D\eta_t(\varphi) \rightarrow \text{id}$ in the strong operator topology as $t \rightarrow 0$. Then a sufficient condition that the composition $\eta_t(\psi_t(\varphi, u))$ be a solution of equation (1) is that $\psi_t(\varphi, u)$ satisfy

$$(3) \quad dv_t/dt = u(t) \sum_{\nu=0}^{\infty} (-t)^{\nu}/\nu! (\text{ad}^{\nu} \mathcal{A}, \mathcal{B})(v_t), \quad v_0 = \varphi.$$

Such decomposition theorems provide the key to the applications of Lie theory to differential equations and control systems, [6], [7].

Let $g : B \rightarrow \mathbb{R}^k$ be continuous and linear, C an operator of the form (2), $\xi_t(\varphi)$ the solution at time t of $dv_t/dt = C(v_t)$, $v_0 = \varphi$ and define $g_*(C_{\varphi}) = \lim_{t \rightarrow 0} d/dt g(\xi_t(\varphi))$. Analogous to the case of control systems on manifolds, we associate with (1) the set of operators

$$(4) \quad \mathcal{J}^1 = \{(\text{ad}^{\nu} \mathcal{A}, \mathcal{B}) : \nu = 0, 1, \dots\}$$

and let $\mathcal{J}^1(\varphi)$ denote the elements of $\mathcal{J}^1$ evaluated at φ .

THEOREM (Local Controllability). - The observation $g : B \rightarrow \mathbb{R}^k$ of system (1) is locally controllable along the reference solution $\eta_t(\varphi)$ corresponding to $u \equiv 0$ (i.e. $g(\eta_t(\varphi)) \in \text{int } g(A(t, \varphi))$ for small $t > 0$) if $\dim. \text{span } g_*(\mathcal{J}^1(\varphi)) = k$.

Proof : Form $\hat{B} = B \times \mathbb{R}^k$; let $w(t) = g(v_t) \in \mathbb{R}^k$ and $\hat{a} \begin{bmatrix} v_t \\ w(t) \end{bmatrix} = \begin{bmatrix} \mathcal{A} v_t \\ g_*(\mathcal{A} v_t) \end{bmatrix}$,
 $\hat{\mathcal{B}} \begin{bmatrix} v_t \\ w(t) \end{bmatrix} = \begin{bmatrix} \mathcal{B} v_t \\ g_*(\mathcal{B} v_t) \end{bmatrix}$. The "augmented system" on $\hat{B}$ is

$$(i) \quad \frac{\partial}{\partial t} \begin{bmatrix} v_t \\ w(t) \end{bmatrix} = \hat{a} \begin{bmatrix} v_t \\ w(t) \end{bmatrix} + u(t) \hat{\mathcal{B}} \begin{bmatrix} v_t \\ w(t) \end{bmatrix}, \quad \begin{bmatrix} v_0 \\ w(0) \end{bmatrix} = \begin{bmatrix} \varphi \\ g(\varphi) \end{bmatrix}.$$

Define $\mathcal{J}^1 \begin{bmatrix} \varphi \\ g(\varphi) \end{bmatrix} = \{ (\text{ad}^\nu \hat{a}, \hat{a}) \begin{bmatrix} \varphi \\ g(\varphi) \end{bmatrix} : \nu = 0, 1, \dots \}$ and $\pi : \hat{B} \rightarrow \mathbb{R}^k$ be projections to $\mathbb{R}^k$, specifically for $\psi \in B$, $y \in \mathbb{R}^k$, $\pi \begin{bmatrix} \psi \\ y \end{bmatrix} = y$. Let $\hat{A}(t, \varphi) \subset \hat{B}$ denote the elements attainable at time t by solutions of (i) corresponding to all admissible controls. The reference solution of (i) corresponding to $u \equiv 0$ is $\begin{bmatrix} \eta_t \\ g(\eta_t) \end{bmatrix} \in \hat{A}(t, \varphi)$. Clearly if $v_t(u)$ denotes a solution of (1) at time t corresponding to control choice u , then $\begin{bmatrix} v_t(u) \\ g(v_t(u)) \end{bmatrix}$ is a solution of (i). It follows that

$$(ii) \quad \pi(\hat{A}(t, \varphi)) = g(A(t, \varphi)).$$

Since $\text{span } \mathcal{J}^1 \begin{bmatrix} \varphi \\ g(\varphi) \end{bmatrix}$ is the "first order local set of directions" in which one can proceed via solutions of (i), from the inverse function theorem (see [8], chap. I. § 5, in particular corollaries 1, 1s) one has

$$(iii) \quad g(\eta_t) = \pi \begin{bmatrix} \eta_t \\ g(\eta_t) \end{bmatrix} \in \text{int } \pi(\hat{A}(t, \varphi)) = \text{int } g(A(t, \varphi))$$

for small $t > 0$ if $\dim \text{span } \pi(\mathcal{J}^1 \begin{bmatrix} \varphi \\ g(\varphi) \end{bmatrix}) = k$. To complete the proof one need only show that $\pi(\mathcal{J}^1 \begin{bmatrix} \varphi \\ g(\varphi) \end{bmatrix}) = g_*(\mathcal{J}^1(\varphi))$ which is a straightforward calculation using induction. ■

As an application, we consider a tension controlled vibrating string. Let ρ denote density, and $s = s(t)$ tension. The one dimensional equation of the vibrating string is $\rho \partial^2 w / \partial t^2 = \partial / \partial x (s(t) \partial w / \partial x)$, where w measures deflection from the rest position. Choose u_0 as a nominal value of $s(t) / \rho$, $u_0 > 0$ such that $u_0 - u > 0$ and the control $u(t) = s(t) / \rho - u_0$, with $|u(t)| \leq u$. Let $\partial w / \partial x = v^1$, $\partial w / \partial t = v^2$ to obtain the first order system

$$(i) \quad \begin{aligned} \partial v^1 / \partial t &= \partial v^2 / \partial x, & v^1(x) &= v^1(x), & 0 \leq x \leq \ell \\ \partial v^2 / \partial t &= u_0 \partial v^1 / \partial x + u(t) \partial v^1 / \partial x, & v^2(x) &= v^2(x), & 0 \leq x \leq \ell \end{aligned}$$

where we assume the string is clamped at both ends so $v^2(0) = v^2(\ell) = 0$. Take $C_0[0, \ell]$ to be those functions in $C[0, \ell]$ which vanish at 0 and ℓ and $B = C[0, \ell] \times C_0[0, \ell]$. The boundary data $w(t, 0) = w(t, \ell) = 0$ is implicit in B

if the constants chosen in recovering w from v^1, v^2 are properly chosen.

This is assumed. With $\mathcal{A} = \begin{bmatrix} 0 & \partial/\partial x \\ u_0 \partial/\partial x & 0 \end{bmatrix}$, $\mathcal{B} = \begin{bmatrix} 0 & 0 \\ \partial/\partial x & 0 \end{bmatrix}$,

$$(ii) \quad \mathcal{J}^1(\varphi) = \{(\text{ad}^v \mathcal{A}, \mathcal{B})\varphi : v = 0, 1, \dots\} = \left\{ \begin{bmatrix} 0 \\ \partial\varphi^1/\partial x \end{bmatrix}, \right.$$

$$\left. \begin{bmatrix} \partial^2 \varphi^1 / \partial x^2 \\ -\partial^2 \varphi^2 / \partial x^2 \end{bmatrix}, \begin{bmatrix} -2\partial^3 \varphi^2 / \partial x^3 \\ 2u_0 \partial^3 \varphi^1 / \partial x^3 \end{bmatrix}, \begin{bmatrix} 2^2 u_0 \partial^4 \varphi^1 / \partial x^4 \\ -2^2 u_0 \partial^4 \varphi^2 / \partial x^4 \end{bmatrix}, \begin{bmatrix} -2^3 u_0 \partial^5 \varphi^2 / \partial x^5 \\ 2^3 u_0 \partial^5 \varphi^1 / \partial x^5 \end{bmatrix}, \dots \right\}.$$

One may now readily check specific initial data and observations for local controllability. For example, if $\varphi^1(x) = (\pi/\ell) \cos(\pi x/\ell)$, $\varphi^2(x) = 0$ the solution with $u(t) \equiv 0$ (i.e. the reference solution) is $w(t, x) = \cos(\sqrt{u_0} \pi t/\ell) \sin(\pi x/\ell)$, i.e. at each time t , the position of the string is a scalar multiple of $\sin(\pi x/\ell)$. Take as observation $g_1(v_1) = v_t^1(\ell/2)$, $g_2(v_t) = v_t^2(\ell/2)$, i.e. respectively the angle of deflection of the string at $\ell/2$ and the velocity of the point at $\ell/2$. Computing shows $\text{rank } g_*(\mathcal{J}^1(\varphi)) = 1$, not 2, hence the theorem does not imply local controllability of this observation. Physically this is expected since the initial data was chosen so that $g_1(v_t)$, the angle of deflection at $\ell/2$, would be zero for all t . On the other hand, the velocity of the point at $\ell/2$, i.e. $g_2(v_t)$, can be locally controlled via tension.

One may show that for any integer k there exists initial data φ^1, φ^2 and an $\mathbb{R}^k$ valued observation g which is locally controllable along the reference via tension.

II. - FINITE DIMENSIONAL DIFFERENTIAL REALIZATIONS.

Consider a special case of equation (1) i.e.

$$(5) \quad dv_t/dt = Cv_t + u(t)b, \quad v_0 = \varphi \in B$$

where C is linear and $b \in B$. By differentiating $g(v_t(u))$ with respect to t it follows that if there exists a mapping $C_* : \mathbb{R}^k$ such that

$$(6) \quad g_* C v_t = C_* g(v_t)$$

then a strong differential realization of g exists. If C has $\ker g$ as an invariant subspace, equation (6) may be used to define C_* . This rather severe restriction leads one to "change the order of events". Given an equation of the form (8), suppose C has an invariant subspace, S , of co-dim k . Then any observation g having S as kernel does admit a strong differential realization. A specific example with entails a slightly more general evolutionary equation than (5) is

Example 2.1. - Consider the parabolic partial differential equation

$$(7) \quad \partial v_t / \partial t = \partial^2 v_t / \partial x^2 + u(t) (\partial v_t / \partial x + \sin x) \\ v_0(x) = 2 \cos x + 2.$$

Let S^1 be the one sphere parametrized by $-\pi \leq x \leq \pi$ and consider equation (7) on $S^1 \times [0, \infty]$. Let $B = \{w \in L_2[-\pi, \pi] : w(-\pi) = w(\pi) = 0\}$, $a v_t = \partial^2 v_t / \partial x^2$, $B v_t = \partial v_t / \partial x$ and $b \in B$ be given by $b(x) = \sin x$. For the observation we choose $g = (g_1, g_2)$ with $g_1(v_t) = \frac{1}{\pi} \int_{-\pi}^{\pi} v_t(x) \sin x dx$, $g_2(v_t) = \frac{1}{\pi} \int_{-\pi}^{\pi} v_t(x) \cos x dx$. Then $S = \text{span}\{1, \sin v x, \cos v x : v = 2, 3, \dots\} = \ker g$ while $\text{codim } S = 2$ and $a, B : S \rightarrow S$. To compute the strong differential realization, let $v_t(x) = \sum_{j=1}^{\infty} \sigma_j(t) \sin jx + \sum_{j=0}^{\infty} \gamma_j(t) \cos jx$ and form the equation $d/dt g(v_t) = g_* a v_t + u(t) g_* B v_t + u(t) g_* b$. Letting $\sigma_1(t) = y_1(t)$, $\gamma_1(t) = y_2(t)$ the differential realization on $\mathbb{R}^2$ is $(\dot{y} = dy/dt)$

$$(8) \quad \begin{aligned} \dot{y}_1 &= -y_1 + u(t) (1 - y_2), \quad y_1(0) = 0 \\ \dot{y}_2 &= -y_2 + u(t) y_1, \quad y_2(0) = 2. \end{aligned}$$

If we consider the problem, for (7), of finding that measurable control u with $|u(t)| \leq 1$ such that $g(v_t) = (0, 1)$ in minimum time t , this leads to the problem of reaching $(0, 1)$ in minimum time by a solution of (8). The method of [9, §22] may be used to show that the optimal solution of this latter "bilinear problem" is $y_1(t) \equiv 0$, $y_2(t) = 2e^{-t}$, a singular arc obtained with control $u(t) \equiv 0$.

-:-:-:-

REFERENCES

- [1] M.Q. JACOBS and C.E. LANGENHOP. - Criteria for Function Space Controllability of Linear Neutral Systems. SIAM J. Control and Opt., 14 (1976), p.1009-1048.
- [2] H.T. BANKS and G.A. KENT. - Control of Functional Differential Equations of Retarded and Neutral Type to Target Sets in Function Space, SIAM J. Control 10 (1972), p.567-594.
- [3] H.R. RODAS and C.E. LANGENHOP. - A Sufficient Condition for Function Space Controllability of a Linear Neutral System. SIAM J. Control and Opt. 16 (1978), p.429-435.
- [4] H. HERMES. - Controllability of Nonlinear Delay Equations. J. Nonlinear Analysis, Theory, Methods & Appl., 3, (1979), pp.483-493.
- [5] H. HERMES. - Local Controllability of Observables in Finite and Infinite Dimensional Nonlinear Control Systems. Applied Math. and Opt., 5, (1979), pp.117-125.
- [6] K.T. CHEN. - Decomposition of Differential Equations. Math. Ann. 146 (1962) p.263-278.
- [7] H. HERMES. - Local Controllability and Sufficient Conditions in Singular Problems II. SIAM J. Control and Opt. 14 (1976), p.1049-1062.
- [8] S. LANG. - Introduction to Differentiable Manifolds. J. Wiley & Sons, Inc. (1967), New-York.
- [9] H. HERMES and J.P. LASALLE. - Functional Analysis and Time Optimal Control. Acad. Press Inc., New-York (1969).

-:-:-:-

Henry HERMES
 Department of Mathematics
 University of Colorado
 Boulder, COLORADO 80309 (U.S.A.)